

## Z-100Plus Automatic Antenna Tuner



### Z-100Plus Automatic Antenna Tuner



### Specifications

LDG's popular Z-100 economy tuner is now the Z-100Plus. Still small and simple to use, the Z-100Plus sports 2000 memories that store both frequency and tuning parameters. It will run on any voltage source from 7 to 18 volts; six AA batteries will run it for a year of normal use. Current draw while tuning is less than 100ma.

- RF Power: 0.1 to 125 watts SSB, CW and digital modes.
- Latching relays for ultra low power consumption
- 2000 memories sorted by frequency.
- 1.8 to 54 MHz coverage (continuous coverage for MARS)
- Tunes 6 to 800 ohms. (16 to 150 on 6M)
- SO-239 in and out connections for dipoles, verticals, beams, G5RV, OCF, Cobra, ect.
- 7 to 18 Volts DC, 100 mA.
- Dimensions: 5.5"L, 5.5"W, 1.5"H. Weight: 16 ounces
- Includes 1 foot Icom and Yaesu 857/897 interface cable and 1 foot coax jumper.



The Z-100Plus now includes an internal frequency counter so the operating frequency is stored with tuning parameters to make memory tunes a blazingly fast 0.1 seconds; full tunes take an average of only 6 seconds.

With all these enhancements, you'd expect to pay more, but once again leading the industry, LDG offers the enhanced Z-100Plus for the low price of \$159.99. Order yours today.

**List Price \$159.99**



### LDG Electronics, Inc.

1445 Parran Rd.

St. Leonard, MD 20685 USA

Phone: 410-586-2177

Fax: 410-586-8475

E-mail: [ldg@ldgelectronics.com](mailto:ldg@ldgelectronics.com)

Web: [www.ldgelectronics.com](http://www.ldgelectronics.com)